

Furnizor: **Sc Trivolt Distribution SRL**  
Reg. com.: J23/3300/2016  
CIF: RO36421140  
Adresa: Strada Apusului nr 3 ( primul  
sens giratoriu Tehodor Pallady-  
Autostrada Soarelui), Catelu, Ilfov  
Banca: BRD  
IBAN: RO34BRDE441SV13182234410

**CAUTION**


1. Please strictly follow the instructions for use;
2. Do not replace the parts and do the transformation of product;
3. Battery in empty state, please charge more than 10hours before using;
4. Connect power but light does not work, please check whether lamps are properly connected to the main;
5. Please strictly use the Emergency kit according to the wiring diagram before connection and pay attention to reverse connection;
6. Please pay attention to the battery electrodes should be connected in right way, which is used to measure electricity;
7. This Emergency kit is only suitable for use in indoor;

**SPECIFICATION**

1. Input Voltage: AC 220-240V 50/60Hz
2. Voltage range: DC 30-42V
3. Maximum Output Power: 20W max
4. Duration time: 3h
5. Emergency switch use time: <1 Second
6. Charging time: <24h
7. Battery capacity: 7.2V 4400mAh Ni-Cd
8. The battery charging and discharging times: >500 times
9. Ambient Temp: Max 50°C
10. Light Source: LED

**WIRE DIAGRAM:**

Caution: Please cut off the power when installation!



**SCHRACK LED EMERGENCY KIT PT V-TAC PANEL 29W - 45W**

EAN-Code 3800157617451

Lungime netă 455,00mm

Lăţime netă 52,00mm

Înălţime netă 33,00mm

Masă netă 1,09kg.

Temperatura minimă a mediului ambiant -20°C

Temperatura maximă a mediului ambiant 45°C

Fabricant 08-V-TAC

Iluminat de siguranţă Emergency kit 3h

Pachete disponibile 1 buc.

Pret: 419,84 lei (TVA inclus)

Detalii online: <https://www.materialelectrice.ro/led-emergency-kit-pt-v-tac-panel-29w-45w-266724>