

Furnizor: **Sc Trivolt Distribution SRL**  
Reg. com.: J23/3300/2016  
CIF: RO36421140  
Adresa: Strada Apusului nr 3 ( primul  
sens giratoriu Tehodor Pallady-  
Autostrada Soarelui), Catelu, Ilfov  
Banca: BRD  
IBAN: RO34BRDE441SV13182234410



### **IEK ARMAT ALARM CONTACT AR-AUX-AC 240...415V**

The ARMAT AUX-AC alarm contact serves to provide information about the status of ARMAT M06N and M10N series circuit breakers in process automation or plant-specific protection systems. The ARMAT AUX-AC serves to signal the position of the cocking mechanism of the ARMAT M06N or M10N series circuit breakers. After the module has been fitted into the cocking mechanism of ARMAT M06N or M10N series switches, the contacts remain in this position when the operating lever is first actuated and when the BA is switched off manually. The contacts will only be switched when the circuit breaker is tripped against overcurrent (overload or short-circuit). Attached without screws to M06N and M10N ARMAT circuit breakers. Compatibility: ARMAT

Nominal rated voltage: 240...415

Number of contacts as change-over contact: 0

Number of contacts as normally open contact: 1

Number of contacts as normally closed contact: 1

Conditional heat current of additional contact: 6.0

Conditional heat current of emergency contact: 6.0

Rated insulation voltage  $U_i$ : 415

Wear resistance: 10000

Degree of protection (IP): EV006405

Type of electric connection: EV000415

Width: 9.0

Height: 81.5

Depth: 75.6

Weight: 36

Rated operation current  $I_e$  at AC-15, 230 V: -

Mounting method: EV003965

Conductor cross section: 1...2,5

Number of fault-signal switches: 2

Pret: 0,00 lei (TVA inclus)

Detalii online: <https://www.materialelectrice.ro/armat-alarm-contact-ar-aux-ac-240-415v-307304>