



LEGRAND 180° SENZOR DE MISCARE -IP40 -8 M -MONTAJ INCASTRAT -CUOUT OVERRIDE -PIR -CARDBOARD

Caracteristici tehnice

2-wire motion sensors, without neutral

IR detection

Accepted Putere by lamp type:

LEDs: 3 to 100 W

compact fluorescent: 3 to 100 W

LEDs, CFLs, Halogen, fluo tubes with ferromagnetic or electronic transformer: 3 to 250 VA

halogen 230 V, incandescent: 3 to 250 W

For LED and compact fluorescent lamps

If several sensors are installed on the same circuit, the minimum load changes: refer to the technical sheet

Possibility to install up to 3 sensors in parallel

Time delay setting from 10 s to 10 min

Light level threshold setting from 5 lux to 1275 lux

Standby Consum : 0.2 W

Sensor without override

Cardboard

Range 8 m

Recommended fixing height: 1.2 m

2-wire without neutral

Light level threshold: 5 to 1275 lux

Adjustable time delay: 10 s to 10 min

Standby Consum: 0.2 W

Caracteristici generale

Mosaic™ Programme mechanisms - motion and presence sensors

All sensors are compatible with any lamp - Detection field: 120°

Detection range: 8 m

Recommended installation height: 1.20 m
Integrated self-protection against overloads and short-circuits.
2 module
Pret: 488,13 LEI (TVA inclus)

Detalii online: <https://www.materialelectrice.ro/1800-senzor-de-miscare-ip40-8-m-montaj-incastrat-cuout-override-pir-cardboard-221715>