



LEGRAND LAMPA DE EMERGENTA U21-AUTOTEST/ADDRESS MAINTAINED/NON MAINTAINED-350 LM-1H-LED

Caracteristici tehnice

Autotest and addressable luminaires - Maintained/Non-maintained (M/NM)

Autotest/addressable luminaires incorporate an automatic self-testing system in order to check the emergency mode

Tests result is visible on 2 signalling LEDs (green-OK and yellow-defective). Addressable function is activated by setting an ID on each luminaire with configuration tool (Cat.No 0 626 10) and wiring a complementary BUS line

Operating state of all addressable luminaires can be centralized by the control interface (Cat.No 0 626 00) and monitored on a local touch screen controller (Cat.No 0 626 01), or with the building's plan on Legrand Vision System (LVS2) PC software (Cat.No 0 626 02)

These Maintained luminaires can also operate in Non-maintained mode according to the wiring of normal lighting

350 lm - 1h (LEDs)

Caracteristici generale

U21 LED - indoor self-contained emergency lighting luminaires LED

LED maintained and Non-maintained units

Certified to IEC and EN60598-2-22 standards

High Putere LEDs

IP 42 - IK 04. Duration: 1 and 3 hours. Ni-Cd or Ni-MH batteries

Recharge time: 24 hours. Charge monitor with a green LED

Tensiune de alimentare: 230 V~ ±10% - 50/60Hz - Class II

High capacity screw terminals (2 x 2.5 mm²)

To install a full IP 65 solution, add IP 65 weatherproof box Cat.No 6 616 16

Montaj incastat in dry partitions (ceiling and wall): add Montaj incastat frame Cat.No 6 617 20. Montaj incastat in masonry (brick or concrete wall): add both Montaj incastat box Cat.No 0 617 21 and Montaj incastat frame Cat.No 6 617 20

Can be equipped with metallic protection grids Cat.Nos 0 626 90/92
Pret: 523,13 LEI (TVA inclus)

Detalii online: <https://www.materialelectrice.ro/lampa-de-emergenta-u21-autotest-address-maintained-non-maintained-350-lm-1h-led-225984>