



BTICINO INTRERUPATOR CONECTAT PENTRU STORURI LIVING NOW WITH NETATMO PENTRU COMANDA LOCALA SAU DE LA DISTANTA

Descoperi? Intrerup?tor conectat pentru storuri Living Now with Netatmo pentru comanda locala sau de la distanta din categoria Casa inteligenta - Gestiune si control, un produs cu codul K4027C. Acesta ofer?

caracteristici excelente: Bus system KNX No

Bus system KNX-RF (Radio Frecvent) No

Bus system radio frecvent Yes

Bus system LON No

Bus system Powernet No

Other bus systems Zigbee

Radio frecvent bidirectional Yes

Mounting method Flush-mounted

Width in number of modular spacings 1

With bus connection No

Bus module detachable No

Local operation/hand operation Yes

With LED indication Yes

Number of inputs 4

Switching current (resistive) 2 A

Max. switching power 500 W

Max. number of venetian-blind outputs 1

With switch function Yes

Type of current AC

Degree of protection (IP) IP20

Min. depth of built-in installation box 40 mm

Width 22 mm

Height 45 mm

Depth 42 mm

Built-in depth 35 mm
Degree of impact strength (IK) IK04
Operating / setting temperature 5-45 °C
Storage temperature 0-45 °C
Nominal voltage 100-240 V
Frequency 50-60 Hz
Standby consumption 0.1 mA
Mandatory neutral Yes
Terminal marking indication Yes
Stress test conformity (1000V) No
Colour Black
RAL-number 9011
Halogen free Yes
Antimicrobial treatment No
Connection type Screwed terminal
Number of terminals 4
Terminals capacity 1.5-2.5 mm²
Contains Batteries and/or Accumulator No
Connected object Yes
Operating method Zigbee
Application store for download App Store , Google Play Store
With voice command Yes
Programmable Yes
Interoperable connection Protocol Yes
Connectable by Internet box Yes
Compatible voice assistants Google Assistant , Amazon Alexa , Apple Siri
Product use function Shutter management
Application name Home + Control
Programming way Smartphone apps. Ideal pentru proiectele tale, asigurand eficienta si calitate superioara.
Pret: 258,70 LEI (TVA inclus)

Detalii online: <https://www.materialelectrice.ro/interruptor-conectat-pentru-storuri-living-now-with-netatmo-pentru-comanda-locala-sau-de-la-distanta>