

Furnizor: **Sc Trivolt Distribution SRL**  
Reg. com.: J23/3300/2016  
CIF: RO36421140  
Adresa: Strada Apusului nr 3 ( primul  
sens giratoriu Tehodor Pallady-  
Autostrada Soarelui), Catelu, Ilfov  
Banca: BRD  
IBAN: RO34BRDE441SV13182234410

### **ERSE CABLU LIY(ST)CY-TP 2 X 2 X 2.5, ERSE**



construc?ie

1. CONDUCTOR IEC-60228, VDE 0295, EN 60228 Clasa-5 din cupru neizolat ELEKTROLYTIC fire subtiri
2. IZOLARE EN 50290-2-26 HFFR combinate
3. Cod culoare DIN 47100
4. E?uare în straturi de bitum OPTIMUM
5. Placarea cu band? de PES
6. SCREEN conserve de sârm? de cupru + TAPE AL-PES
7. MANTAUA EN 50290-2-27 HFFR combinate
8. MANTAUA CULOARE RAL 7001 GREY

cei care nu

- GOOD EMC \* CHARACTERISTICI
- Ignifug CHARACTERISTICA
- Fumigen
- F?R? gaze otr?vite ?i corozive

Caracteristici tehnice

1. CONDUCTOR REZISTEN?A  $0,22 \text{ mm}^2 = 79 \Omega / \text{km}$   
 $0,34 \text{ mm}^2 = 56 \Omega / \text{km}$   
 $0,50 \text{ mm}^2 = 39 \Omega / \text{km}$   
 $0,75 \text{ mm}^2 = 26 \Omega / \text{km}$   
 $1,0 \text{ mm}^2 = 19,5 \Omega / \text{km}$   
 $1,5 \text{ mm}^2 = 13,3 \Omega / \text{km}$   
 $2,5 \text{ mm}^2 = 7,98 \Omega / \text{km}$
2. Rezisten?ei de izola?ie  $0,22 \text{ ?i } 0,34 \text{ mm}^2 = 200 \text{ mW. Km}$   
 $> 0,50 \text{ mm}^2 = 20 \text{ mW. Km}$
3. MUTUAL CAPACITATE  $0,22 \text{ mm}^2 = 100 \text{ PF / m}$   
 $0,34 \text{ mm}^2 = 110 \text{ PF / m}$   
 $0,50 \text{ mm}^2 = 120 \text{ PF / m}$   
 $0,75 \text{ mm}^2 = 120 \text{ PF / m}$   
 $1,0 \text{ mm}^2 = 130 \text{ PF / m}$   
 $1,5 \text{ mm}^2 = 140 \text{ PF / m}$   
 $2,5 \text{ mm}^2 = 150 \text{ PF / m}$
4. Impedanta (aprox.)  $78 \Omega$
5. INDUCTAN?A (aprox.)  $0,67 \text{ mH / km}$
6. Curentul de sarcin?  $0,22 \text{ mm}^2 = 2,5 \text{ A}$   
 $0,34 \text{ mm}^2 = 4,5 \text{ A}$   
 $0,50 \text{ mm}^2 = 6,0 \text{ A}$   
 $0,75 \text{ mm}^2 = 13 \text{ A}$   
 $1,0 \text{ mm}^2 = 16 \text{ A}$   
 $1,5 \text{ mm}^2 = 20 \text{ A}$   
 $2,5 \text{ mm}^2 = 25 \text{ A}$
7. Tensiune de  $0,22 \text{ am } 0,34 \text{ mm}^2 = 250 \text{ V}$   
 $> 0,50 \text{ mm}^2 = 300/500 \text{ V.}$
8. Tensiunea de testare  $0,22 \text{ ?i } 0,34 \text{ mm}^2 = 1000 \text{ V}$   
 $> 0,50 \text{ mm}^2 = 300/500 \text{ V.}$
9. Indoire 15X cablu Ø
10. Interval de temperatur?  $-30 \text{ }^\circ \text{C} \sim +70 \text{ }^\circ \text{C}$
11. FLACARA TEST IEC 60332-1-2, VDE 0482-332-1-2 EN 60332-1-2
12. FUM DENSITATE IEC 61034-2/VDE 0482-1034-2 EN 61034-2
13. Test pe corozivitatea gaze de ardere IEC 60754-2/VDE 0482-267-2-3 EN 50267-2
14. HALOGEN test gratuit IEC 60754-1/VDE 0482-267-2-3 EN 50267-2-3
15. EMC \* EMC \* = COMPATIBILITATE ELECTROMAGNETIC?

Pret: 0,00 lei (TVA inclus)

Detalii online: <https://www.materialeelectrice.ro/cablu-liy-st-cy-tp-2-x-2-x-2-5-erse-18180>