

Furnizor: **Sc Trivolt Distribution SRL**  
Reg. com.: J23/3300/2016  
CIF: RO36421140  
Adresa: Strada Apusului nr 3 ( primul  
sens giratoriu Tehodor Pallady-  
Autostrada Soarelui), Catelu, Ilfov  
Banca: BRD  
IBAN: RO34BRDE441SV13182234410



**LEGRAND AUTOMATIC SWITCH ARTEOR - CU NEUTRAL - 3-WIRE -  
1000 W- 2 MODULE - CHAMPAGNE**

Caracteristici tehnice

Motion sensors

Measurement of luminosity threshold

Adjustment of luminosity threshold and time delay

Max. lux and min. time delay factory pre-set

Recommended fixing height: 1 m

IR detection 180°

Adjustable luminosity threshold: 5 to 1275 lux

Installation in box min. depth 40 mm recommended

2 module

Range 8 m

With neutral, 3-wire - 2000 W

Operates:

2000 W incandescent and halogen lamps 230 V~

1000 VA ELV halogen lamps with ferromagnetic or electronic transformer

500 VA compact fluorescent lamps

0 to 250 W for LEDs

Settings modified on the device via thumbwheel or configuration tool Cat.Nos 0 882 30  
and 0 882 35

Time delay adjustable from 5 s to 30 min

Champagne

Caracteristici generale

Arteor™ motion sensors

Mechanisms supplied with rocker plates, to be equipped with support frames and plates

Pret: 0,00 lei (TVA inclus)

Detalii online: <https://www.materialeelectrice.ro/automatic-switch-arteor-cu-neutral-3-wire-1000-w-2-module-champagne-222778>