

Furnizor: **Sc Trivolt Distribution SRL**
Reg. com.: J23/3300/2016
CIF: RO36421140
Adresa: Strada Apusului nr 3 (primul
sens giratoriu Tehodor Pallady-
Autostrada Soarelui), Catelu, Ilfov
Banca: BRD
IBAN: RO34BRDE441SV13182234410



IEK ARMAT SHUNT TRIP INDICATED AR-AUX-SR-I 100-415V

ARMAT Series AUX-SR independent trip units are designed for remote tripping of ARMAT M06N and M10N series circuit breakers. Attached without screws to M06N and M10N ARMAT circuit breakers. Device fitting: EV000028

Additional equipment: EV009772

Assembly width (TE): 17,7

Number of normally open contacts: 1

Number of normally closed contacts: 0

Number of change-over contacts: 0

Number of contacts as change-over contact: 0

Number of fault-signal switches: 1

Rated switch current: 6

Control voltage type: EV000509

Nominal rated voltage: 100...415

Nominal voltage DC: 110...130

Voltage type: EV000509

Compliance with current breakers: ARMAT

Conventional thermal current : 6

Construction type: EV008723

Operating temperature range: -5...40

Max. conductor cross section: 2,5

Width: 17.7

Height: 82.7

Depth: 75.6

Mounting method: EV000154

Mechanical wear resistance: 20000

Attachment Side to Authomatic current breaker: IEK_V0000367

Time off at min of actuation voltage: 0,01

Time off at max of actuation voltage: 0,01

Operation mode: IEK_V0000393

Range of actuation voltage: 70...456,5

Wear resistance: 20000

Type of electric connection: EV000415

: 110...130

Pret: 0,00 lei (TVA inclus)

Detalii online: <https://www.materialelectrice.ro/armat-shunt-trip-indicated-ar-aux-sr-i-100-415v-307311>