

Furnizor: **Sc Trivolt Distribution SRL**
Reg. com.: J23/3300/2016
CIF: RO36421140
Adresa: Strada Apusului nr 3 (primul
sens giratoriu Tehodor Pallady-
Autostrada Soarelui), Catelu, Ilfov
Banca: BRD
IBAN: RO34BRDE441SV13182234410



IEK SHUNT TRIP RN47-60M PENTRU VA47-60M

The RN47-60M shunt release is designed for remote tripping function of V Δ 47-60M series circuit breaker. Attached without screws to VA47-60M circuit breakers. Device fitting: EV000646

Additional equipment: EV009614

Assembly width (TE): 1

Number of normally open contacts: 0

Number of normally closed contacts: 0

Number of change-over contacts: 0

Number of contacts as change-over contact: 0

Number of fault-signal switches: 0

Rated switch current: 0,011

Control voltage type: EV000460

Nominal rated voltage: 230

Compliance with current breakers: Δ ' Δ 47-60 Δ ∞

Operating temperature range: -40...50

Max. conductor cross section: 1...2,5

Width: 18.0

Height: 80.0

Depth: 65.5

Mounting method: EV004369

Mechanical wear resistance: 10000

Attachment Side to Authomatic current breaker: IEK_V0000367

Electric wear resistance: 4000

Operating voltage range: 161...253

Operation mode: IEK_V0000368

Power consumption: 3.0

Type of electric connection: EV000415

Pret: 0,00 lei (TVA inclus)

Detalii online: <https://www.materialelectrice.ro/shunt-trip-rn47-60m-pentru-va47-60m-307455>