

Furnizor: **Sc Trivolt Distribution SRL**
Reg. com.: J23/3300/2016
CIF: RO36421140
Adresa: Strada Apusului nr 3 (primul
sens giratoriu Tehodor Pallady-
Autostrada Soarelui), Catelu, Ilfov
Banca: BRD
IBAN: RO34BRDE441SV13182234410



IEK ALARM CONTACT AKM-400E/630E (AKM-39) PENTRU MCCB 88-39 WITH MCU MASTER

Signal auxiliary contact AKm is intended for giving out a signal when a circuit breaker actuates VA88 MASTER from: - overcurrent (overload or short circuit); - shunt trip; - undervoltage trip; - "TEST" button. Ease of use.

Guaranteed impossibility of simultaneous switching on of two VA88 MASTER circuit breakers. Compatibility: 88 NĐμN€Đ, Đ, MASTER

Nominal rated voltage: AC: 230/400; DC: 220

Number of contacts as change-over contact: 2

Number of contacts as normally open contact: 1

Number of contacts as normally closed contact: 1

Nominal current AC-15 with nominal operating voltage 230V: 1.00

Nominal current AC-15 with nominal operating voltage 400V: 1.00

Nominal current DC-13 with nominal operating voltage 230V: 0.20

Conditional heat current of emergency contact: 3.0

Rated insulation voltage U_i : 690

Type of electric connection: EV000415

Width: 40.0

Height: 50.0

Depth: 50.0

Rated operation current I_e at AC-15, 230 V: 1.0

Mounting method: EV003964

Conductor cross section: 0,2

Pret: 0,00 lei (TVA inclus)

Detalii online: <https://www.materialelectrice.ro/alarm-contact-akm-400e-630e-akm-39-pentru-mccb-88-39-with-mcu-master-307596>