

Furnizor: **Sc Trivolt Distribution SRL**  
Reg. com.: J23/3300/2016  
CIF: RO36421140  
Adresa: Strada Apusului nr 3 ( primul  
sens giratoriu Tehodor Pallady-  
Autostrada Soarelui), Catelu, Ilfov  
Banca: BRD  
IBAN: RO34BRDE441SV13182234410



**IEK ALARM CONTACT AKM-800E (AKM-40) PENTRU MCCB VA88-40  
WITH MCU MASTER**

Signal auxiliary contact AKm is intended for giving out a signal when a circuit breaker actuates VA88 MASTER from: - overcurrent (overload or short circuit); - shunt trip; - undervoltage trip; - "TEST" button. Ease of use.

Guaranteed impossibility of simultaneous switching on of two VA88 MASTER circuit breakers. Compatibility: 88 NµNµ, MASTER

Nominal rated voltage: AC: 230/400; DC: 220

Number of contacts as change-over contact: 2

Number of contacts as normally open contact: 1

Number of contacts as normally closed contact: 1

Nominal current AC-15 with nominal operating voltage 230V: 1.00

Nominal current AC-15 with nominal operating voltage 400V: 1.00

Nominal current DC-13 with nominal operating voltage 230V: 0.20

Conditional heat current of emergency contact: 3.0

Rated insulation voltage  $U_i$ : 690

Type of electric connection: EV000415

Width: 40.0

Height: 50.0

Depth: 50.0

Rated operation current  $I_e$  at AC-15, 230 V: 1.0

Mounting method: EV003964

Conductor cross section: 0,2

Pret: 0,00 lei (TVA inclus)

Detalii online: <https://www.materialelectrice.ro/alarm-contact-akm-800e-akm-40-pentru-mccb-va88-40-with-mcu-master-307651>