



WAGO SPARE SUPPLY TERMINAL BLOCK; 16 MM²; 12 MM; PUSH-IN CAGE CLAMP®; 16,00 MM²; BLUE

Tensiune nominala (III/3): 800; V

Tensiune nominala de supratensiune (III/3): 8; kV

Curent nominal: 76; A

Tehnologie conexiune: Push-in CAGE CLAMP®;

Tip actionare: Push-in; Open Tool Slot;

Connectable conductor materials: Copper;

Nominal cross-section: 16 mm²;

Solid conductor: 0,5 ... 16 mm² / 20 ... 6 AWG;

Solid conductor; push-in termination: 6 ... 16 mm² / 14 ... 6 AWG;

Fine-stranded conductor: 0,5 ... 25 mm² / 20 ... 4 AWG;

Fine-stranded conductor; with insulated ferrule: 6 ... 16 mm² / 10 ... 6 AWG;

Fine-stranded conductor; with ferrule; push-in termination: 6 ... 16 mm² / 10 ... 6 AWG;

Strip length: 18 ... 20 mm / 0.71 ... 0.79 inch;

Numar total de conexiuni: 2;

Total number of potentials: 1;

Numar nivele: 1;

Wiring type: Front-entry wiring;

Note (conductor cross-section): Depending on the conductor characteristic, a conductor with a smaller cross-section can also be inserted via push-in termination.;

Number of jumper slots: 2;

Latime: 12 mm / 0.472 inch;

Inaltime from upper-edge of DIN-rail: 40,8 mm / 1.606 inch;

Adancime: 85,7 mm / 3.374 inch;

Design: angled;

Tip montaj: DIN-35 rail;

Marking level: Center/side marking;

Culoare: blue;
Material izolator: Polyamide 66 (PA 66);
Greutate: 43,6; g
Tip ambalare: BOX;
Tara de origine: PL;
GTIN: 4055143622813;
Customs tariff number: 85369010000;
Pret: 33,74 LEI (TVA inclus)

Detalii online: <https://www.materialeelectrice.ro/spare-supply-terminal-block-16-mm2-12-mm-push-in-cage-clamp-16-00-mm2-blue-152186>