





## LEGRAND 180° SENZOR DE MISCARE MOSAIC - 15 M<sup>2</sup> - DUAL-TECH - VACANCY MODULE CU NEUTRAL - ALB

Caracteristici tehnice 3-wire presence sensor, with neutral Infrared and ultrasonic double technology Allows a precise presence detection. Checks the light level continuously and not only at the time of detection Propose a special mode: manual switching on with integrated pushbutton, automatic switching off Accepted Putere by lamp type: LEDs: 0 to 250 W Compact fluorescent: 0 to 250 W LEDs, CFLs, Halogen, fluo tubes with ferromagnetic or electronic transformer: 0 to 1000 VA Halogen 230 V, incandescent: 0 to 2000 W Up to 10 sensors can be connected in parallel Additional remote manual control possible with push button Time delay setting from 5 s to 30 min Light level threshold setting from 5 lux to 1275 lux Standby Consum : 0.4 W Mosaic With neutral Caracteristici generale Mosaic<sup>TM</sup> Programme mechanisms - motion and presence sensors All sensors are compatible with any lamp - Detection field: 120° Detection range: 8 m Recommended installation height: 1.20 m Integrated self-protection against overloads and short-circuits. 2 module Pret: 721,27 LEI (TVA inclus)

Detalii online: https://www.materialeelectrice.ro/1800-senzor-de-miscare-mosaic-15-m2-dual-tech-vacancy-module-cu-neutral-alb-221720