



## **LEGRAND 3-WIRE SENZOR DE MISCARE MOSAIC - CU NEUTRAL - IR DETECTION - 2000 W - ALU**

### Caracteristici tehnice

3-wire motion sensors, with neutral

IR detection - 2000 W

Checks the light level continuously and not only at the time of detection

Accepted Putere by lamp type :

LEDs: 0 to 250 W

Compact fluorescent: 0 to 250 W

LEDs, CFLs, Halogen, fluo tubes with ferromagnetic or electronic transformer: 0 to 1000 VA

Halogen 230 V, incandescent: 0 to 2000 W

Up to 10 sensors can be connected in parallel

Additional remote manual control possible with push button

Time delay setting from 5s to 30 min

Light level threshold setting from 5 lux to 1275 lux

Standby Consum : 0.2 W

Alu

### Caracteristici generale

Mosaic™ Programme mechanisms - motion and presence sensors

All sensors are compatible with any lamp - Detection field: 120°

Detection range: 8 m

Recommended installation height: 1.20 m

Integrated self-protection against overloads and short-circuits.

2 module

Pret: 474,58 LEI (TVA inclus)

Detalii online: <https://www.materialelectrice.ro/3-wire-senzor-de-miscare-mosaic-cu-neutral-ir-detection-2000-w-alu-222297>