



HAGER MODUL 4 INTR?RI ANALOGICE

Arhitectur?

Sistem bus: KNX

Tip produs: Modul de baz?

Tip de montaj: REG

Comenzi ?i indicatori

Led de semnalizare: Da

? ?????????? ?????????????????????? ? ??????? ??????????????

Conec?ititate

? ?????????? ?????????????? AST: ? ?????????? ??? ?????????????? ?????????? ???????

? ?????????? ?????????: DIN IEC 381-1, -2

???? 4-20 ?? ????? ?????????????????? ?? ?????? ????????

? ?????????? ??? ?????? ?????????? ????????

? ?????????? ??? ?????? ?????????????? ?? ?????????? ??????-???

Voltaj

Tensiune auxiliar?: 24 V AC

Tensiune de intrare: Nu

Tensiune, intr?ri: 0-1; 0-10 V

Tensiune de func?ionare bus: 21 ... 32 V DC

Curent electric

Intr?ri, curent: 0-20; 4-20 mA

Num?rul circuitelor electrice de intrare: 4

Unitate curent de intrare: Nu

Putere

Consum curent: 170 mA

Putere disipat? total? in condi?ii de curent nominal: 6 W

Rezisten??

Impedan?? de intrare, curent: 100 ?

Impedan?? de intrare, voltaj: 18 k?

M?sur?

Valori limit?: per_channel 2

Detector

Curent ie?ire senzor: max 100 mA

Tensiune ie?ire senzor: 24 V DC

??? ??????? ????????

??? ?????????? ??????? ??????, ?????, ??????????, ???????????, ?????????? ? ??????????? ????????

Dimensiuni

Adancime: 70 mm

In?l?ime: 90 mm

L??ime: 72 mm

In?l?ime asamblare de la ?ina DIN: 63 mm

L??ime dispozitiv montat pe ?in? (RMD): 4 modules

Control LED

cu LED verde/ro?u

Conexiune

cu terminal cu ?urub

conexiune bus via terminal conectare

Set?ri

Tipuri de configurare acceptate: system

Accesorii incluse

?????????? 4-? ?????????? ??????? ????????

Echipament

??? ??????????: ??? ??????????: ?????????? ????, 4-???????

Protec?ie

Tip de protec?ie IP: IP20

Condi?ii de utilizare

Temperatur? lucru: -5 ... 45 °C

Identificare

??? ??????????: ??? ??????????: ????????????????

Linie principal? proiectare: instabus KNX/EIB

Instruc?iuni

Necesit? surs? auxiliar? de 24V

Pret: 2.868,20 LEI (TVA inclus)

Detalii online: <https://www.materialelectrice.ro/modul-4-intrari-analogice-242855>